

DCNM-CBCPLR Cable coupler

DICENTIS



The DICENTIS cable coupler enables Technicians to connect DICENTIS cable assemblies (with one another or with standard CAT-5 cable) without the need for special tools.

The cable coupler can be used to:

- Connect two DICENTIS cables so you can easily increase cable length.
- Connect two DICENTIS cables, where one is always present and ends in a “floor pod” and the other cable is only connected when it is required (for example, a rostrum microphone which will not always be used). The cable coupler can be fixed with screws to the floor pod.
- Interconnect DICENTIS cable with standard CAT5-E cable and power cable so you can comply with local regulations or make use of current available infrastructure.
- Interconnect DICENTIS cable with standard CAT5-E cable and a 48VDC power supply close to the devices.
- Create a circuit to power on a system without the need of a Multimedia device, a PC running the Meeting application, or Synoptic control.

Functions

- Makes it easier to adjust cables to the required length when installing rental systems. Offers a means to create cables for the desired length by just interconnecting standard cables without the need for special tools.

- ▶ Provides an easy way to interconnect DICENTIS cable assemblies
- ▶ Provides an easy way to interconnect DICENTIS cables assemblies with non-DICENTIS cable
- ▶ Provides an easy way to create a connection for temporary devices, like a rostrum microphone
- ▶ Provides an easy way to use an external power supply for your devices

- Makes it easy to connect “temporary” devices (for example, a rostrum microphone) to the DICENTIS system. At the location of the rostrum microphone, the cable coupler is used as the endpoint of the cable (mounted in a floor pod).
- Makes it possible to comply to the most stringent norms for fixed/installation cable in buildings. Enables you to use standard CAT-5E and power cable for the part where the norms have to be met, and DICENTIS cable in the conference room.
- Makes it easy to re-use existing infrastructure/networks (for example, if a CAT-5E network is already in place).
- Makes it possible to place a 48 VDC power supply (not part of the Bosch portfolio) close to the participant devices.

Requirements for the power supply:

- nominal output of 48 VDC (ranging from 47 - 49 VDC).
- the ripple should be less than 200 mV pk-pk.
- maximum output current should not exceed 3.0 A (or limited to 3.0 A, because DICENTIS cables and devices have a maximum rating for this current).

Advice

- It is strongly advised that the power supply has its own short circuit protection with a short circuit output current ranging from 4.3 to 5.0 A.
- When the power supply has an automatic restart after a short circuit, this restart function should have an interval time of 3 to 4 seconds and should have no more than 4 restart attempts.
- Upon powering off the power supply, the output should be less than 9 V, 1 mA.

Certifications and approvals

Region	Regulatory compliance/quality marks	
Europe	CE	DECL EC DCNM-CBCPLR

Parts included

Quantity	Component
6 pcs	DCNM-CBCPLR Cable couplers

Technical specifications

Electrical

Supply voltage	48 VDC (ranging from 47 - 49 VDC)
Ripple	< 200 mV pk-pk
Maximum input current	3.0 A

Mechanical

Mounting	Using two 2.5 mm screws
Dimensions (H x W x D)	23 x 77 x 29 mm (0.90 X 3.03 x 1.14 in)
Weight	0.035 kg (0.077 lb)
Color	Jet black (RAL 9005)

Ordering information

DCNM-CBCPLR Cable coupler

To create connections between DICENTIS cable assemblies.

Order number **DCNM-CBCPLR | F.01U.335.531**

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, LLC
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia